(51) International Patent Classification⁷: H05B 33/08

(21) International Application Number: PCT/IB02/00773

(22) International Filing Date: 14 March 2002 (14.03.2002)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
09/810,142 16 March 2001 (16.03.2001) US

(71) Applicant: KONINKLIJKE PHILIPS ELECTRON-ICS N.V. [NL/NL]; Groenewoudseweg 1, NL-5621 BA Eindhoven (NL).

(72) Inventors: MUTHU, Subramanian; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL). CHANG, Chin; Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(74) Agent: DUSSELDORP, Jan, C.; Internationaal Octrooibureau B.V., Prof. Holstlaan 6, NL-5656 AA Eindhoven (NL).

(81) Designated States (national): CN, JP.

(84) Designated States (regional): European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR).

Published:
— with international search report
— before the expiration of the time limit for amending the claims and to be republished in the event of receipt of amendments

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

(54) Title: APPARATUS FOR CONTROLLING A LIGHT SOURCE



(57) Abstract: A device for controlling and adjusting a display light for a retail display system comprising a computer associated with plural light sources for adjusting the light sources to optimally display particular products. The light sources are adjusted based upon a prestored table specifying optimal lighting conditions for each of plural products, and a feedback loop that feeds back actual lighting conditions.

Apparatus for controlling a light source

This invention relates to commercial display systems and the like, and more
particularly, to an improved apparatus for lighting such commercial display systems and the
like. The invention has particular applications in commercial refrigeration systems used in a
retail environment, such as retail display freezers.

5

Red-Green-Blue (RGB) based white Light Emitting Diode ("LED")
illumination is known in the art and is finding applications in backlighting for LCD panels,
lighting for commercial freezers, signage etc. For these applications, linear power supplies or
10     switch-mode power supplies are used to drive the LEDs. The efficiency of the overall system
with the use of linear power supply is low and the switch-mode power supply overcomes this
problem. Since there are three LED light sources, three independent power supplies are used
to drive the LEDs with a proper current control scheme. In this configuration, each power
supply may contain independent AC/DC converter, a power factor correction unit, an
15     isolation transformer, and a DC/AC converter system. There exists a redundancy in this
scheme due to the three independent AC/DC converters, power factor correction unit, and the
isolation transformer. In addition, it requires independent control of the converters in the
power supplies. This scheme results in increase in cost, complexity in control and poor
performance.
20             A still further problem with the present state of the art is accurately controlling
the amount of each type of light emitted. More specifically, the color of the light resulting
from the combination of the light emitted by the red, green, and blue lights is determined
largely by the relative amounts of each type of light that gets mixed together. The light
source associated with each type of light has a different sensitivity to age and temperature, as
25     well as other factors. As a result, maintaining the appropriate amount of each color of light
such that the resultant total light amount is correct is a difficult if not impossible task.
               Another issue not addressed by prior systems is the fact that in a display case
or retail display refrigeration device, the type and amount of light used to display particular
products may influence a consumer's purchasing decisions. There exists no technique of

uniformly assuring that each specific product is displayed using the optimum lighting conditions.

5          The above and other problem of the prior art are overcome in accordance with the present invention which relates to an LED current driver for a lighting system applicable in commercial displays. In accordance with the invention, drivers are utilized to drive red, green, and blue LEDs in a specified proportion with one another. A feedback loop transmits color and intensity information to a microprocessor, which adjusts the values of each of the
10        red, green, and blue lights to achieve a prescribed lighting intensity and color.

           In an enhanced embodiment, a computer and storage are provided for determining the intensity and color of light used based upon specific products being displayed, or specific times of day. Specifically, a computer may adjust the light color and/or intensity to optimize display at particular times or for particular products. In one exemplary
15        embodiment, a microprocessor controlled AC distributed power supply system is used to provide LED drive currents to a white LED luminary for lighting commercial freezers. The AC distributed system contains a front-end AC/DC converter with power factor correction, a high frequency inverter, an isolation transformer and three DC/AC converters with RGB drive current control system. A single, front-end AC/DC converter system converts the AC
20        supply and maintains a constant DC link voltage as the input to the high frequency DC/AC inverter. The AC/DC converter also performs the power factor correction at the AC mains. The high frequency converter converts the DC voltage to AC and supplies powers to three AC/DC converters with LED drive current control.

           The power converter system is controlled by a microprocessor system. The
25        microprocessor system provides an integrated closed loop control and the PWM generation for the converter systems, in addition to the control of the white light generated by the LED luminary. This approach provides an integral solution for the control of the LED driver system. The control algorithm for the microprocessor system is developed for modularity and with multi-processing features, to provide the effective controlling capabilities for the
30        microprocessor system.

           The microprocessor system is also optionally connected to a user computer, which is programmed with the food that will be displayed in the freezers. The computer in the shop selects the suitable white color point and the lighting level that should be generated by the system when a specified food is being displayed in the freezers, based upon

programmed user priorities. The computer supplies this information to the microprocessor

system at the appropriate times, which controls the driver system to produce the required

color and lighting level. Therefore, the selection of the color and lighting level for the

displayed food is automated. The computer can also start and stop the freezer driver such that

5      the freezer lights are switched off automatically when it is not needed, and therefore, the

power saving is achieved.

In another enhanced embodiment, the system is arranged to accept data from

10     an input device, such as a hand held keyboard or bar code scanner.

Fig. 1 represents a block diagram overview of the exemplary embodiment of

the present invention;

Fig. 2 depicts a representation of a distributed power supply for use in

connection with the present invention;

15     Fig. 3 shows a second embodiment of a distributed power system for use in

driving the lights in accordance with an exemplary embodiment of the present invention; and

Fig. 4 shows the user interface for selecting a particular color for the lighting

system.

20

Fig. 1 presents the overview of the microprocessor controlled AC power

supply system for RGB LED based freezer driver in accordance with an exemplary

embodiment of the invention. The power is supplied by front-end AC/DC converter 10, high

frequency DC/AC converter 20, and three load-end AC/DC converters 30, 31 and 32 for

25     providing RGB LED drive currents. The system includes Red, Green and Blue LED light

sources 120, 130 and 140 respectively. Each Red, Green and Blue LED light source is made

of a plurality of LEDs connected in a suitable series and/or parallel configuration.

The light source also houses light sensors such as photo-diodes and heat-sink

temperature sensors (not shown) for closed-loop feedback control of the white light. The light

30     output of the light source may be supplied to mixing optics and an optical fiber system for

transmission of the light into the freezer or similar environment. However, any suitable

means of conveying the light is acceptable.

The system is controlled by a Microprocessor system 50. The Microprocessor

system uses feedback system 62 to convey variables to the Microprocessor 50. Control

signals are provided to PWM generation and isolation 61 as shown for use in controlling DC/AC converter 20. By adjusting the amplitude and/or duty cycle of the PWM signal produced, the power to each driver 30-32 is adjusted.

The microprocessor system is connected to a user interface and a messaging display system 64. The microprocessor system is also interfaced to an optional computer 51, or to the computer network 53 either via infrared communications or though series/parallel ports 52.

The primary function of the front-end AC/DC converter 10 is to convert the AC supply voltage to a DC voltage. In addition, the AC/DC converter 10 is made to perform the power factor correction at the AC mains, possibly with universal voltage range input. The front-end AC/DC converter 10 can be based on Flyback or Boost topologies.

The feedback control system for the output voltage and the power factor correction at the AC mains is carried out by the microprocessor 50 which outputs the necessary control signals via the PWM generation and the isolation block 61. The PWM gating signals are also generated by the microprocessor 50. For this, the line current is also one of the feedback variables in addition to the DC link voltage. This is shown at 62.

The microprocessor 50 then directly provides the PWM gating signals to the AC/DC converter 10. Alternatively, the power factor correction and the PWM function can be carried out externally. In this case, the AC/DC converter contains the necessary function blocks for the PFC and the PWM generation.

The output of the AC/DC converter system is connected to the input section of the high frequency DC/AC inverter system 20. The DC/AC converter system converts the DC voltage to a high frequency AC voltage. The DC/AC converter is realized either by resonant converter or a square wave converter topology. As an example, the DC/AC converter system based on a resonant converter topology is shown in Fig. 2. In Fig. 2, the resonant converter system is based on the half bridge converter system 202 connected to a resonant tank 201. Alternatively, a full bridge configuration can also be used. The output of the converter is fed to a suitable resonant tank, whose output is connected to a high frequency isolation transformer 203. The transformers then drive converters 30-32 as shown.

Certain simplifications are possible for particular applications. For example, when the light output level is not high, some single stage circuits could be utilized. Figure 3 shows an additional embodiment of the power supply system of Fig. 2. The arrangement of Fig. 3 includes three Flyback converters operated with unity power factor correction,

connected in parallel. In this case, the AC distributed system is realized at the line frequency of the input voltage. Such system is also controlled by microprocessor 50.

Returning to Fig. 1, the outputs of the AC/DC converters 30-32 are connected to the RGB LED light sources, and provide regulated drive currents to the LED light sources
5       120, 130 and 140. The RGB LED light sources may be supplied either with the constant DC current or by PWM current pulse. The magnitude of the DC current or the duty ratio of the PWM current pulses is determined by a white light control system in order to control the color and the lighting level of the white light in accordance with known techniques. The control system is also executed by the microprocessor.

10          A suitable light sensor 40 and a heat sink temperature sensor 41, as shown in Fig. 1, are used to sense the light output and the heat sink temperature of the LEDs. These parameters are fed into the microprocessor 50, through feedback circuit 62. The microprocessor 50 calculates the color and the lighting level of the white luminary. Then, the microprocessor 50 obtains the required LED drive currents or the PWM gating pulse widths.

15      The AC/DC converter is then controlled to provide the required LED drive currents.

For inputting the feedback signals into the microprocessor system, the feed back circuit 62, is used. The feed back circuit 62 includes sensing and conditioning circuits for inputting the feed back signals directly to the analog-to-digital converter 161 in the microprocessor system 50. The feed back variables may comprise the LED light source

20      output from LEDs 120, 130 and 140, heat sink temperature from sensor 41, LED drive currents, DC link voltages, and/or line currents.

The feed back circuit also contains fault-sensing circuits, which generate interrupts upon a fault. The outputs of the fault sensing circuits are directly connected to non-maskable interrupts in the microprocessor system.

25          The microprocessor 50 directly provides the PWM gating signals, which are first passed through an isolation circuit 61. The outputs of this isolation circuit are fed into individual MOSFET drivers in AC/DC converter 10, DC/AC converter 20, and LED drivers 30,31,and 32.

The microprocessor 50 is also connected to a user interface system 63, for

30      manually selecting the color and the lighting level for the white light. An exemplary embodiment of the user interface system is shown in Fig. 4, which comprises switches 401-403 and switch decoding logic 404. When the switch is closed, the decoding logic 404 detects the switch closure and outputs the data in digital form. The output of the decoding logic can be interfaced to the microprocessor using either infrared communications or via

6

cables or other means. The user interface 64 also contains an ON/OFF switch 401 for starting
and stopping the system, and switches 401 for selecting color and light level.

5
The microprocessor 50 is also connected to a message display system 64,
which is used to display the status of the microprocessor system such as the selected color,
system condition, and the lighting levels.

The microprocessor 50 may include at least one CPU or a DSP 160, analog
interface devices 161 such as analog-to-digital converter and digital-to-analog converter
system, digital interfaces 162 such as serial input/output, infrared port, JTAG interface,
digital ports, and other devices 163 such as memory, timers and a clock. A multi-processor

10
system with more than one microprocessor can be used if all the control functions and the
PWM generation are implemented in the microprocessor system.

The output of the feed back circuit 62 for sensing light, LED drive currents,
and the DC link voltage are input to the analog-to-digital converters 161, which converts the
analog signals to digital for the use by the control algorithms.

15
The microprocessor system is also connected to a computer 51, which contains
the information about the food, and the time and the date of the food that will be displayed in
the freezer. The computer is also programmed to select a proper white color point and the
lighting level based on the food that will be displayed. The microprocessor system can be
interfaced to this computer either via an infrared port, or through a serial port or parallel port

20
or a JTAG connector. The microprocessor system is properly equipped with a suitable
interfacing system to handle such connectivity. The computer then supplies the information
for the color and the lighting level of the white light depending on the food that is being
displayed. Therefore, the selection of the color and dimming level for the white light is
automated and the appropriate white light is automatically generated based on the food.

25
The computer also contains the information about the operational hours for the
shop. Therefore, it can start the LED freezer light source when the shop is opened and shut
down the driver when the shop is closed. This arrangement results in automatic power
savings.

Alternatively, rather than use time, the computer may either locally store or

30
access a database of all products. When the user puts product into a freezer, he/she scans it
into the computer using an optional bar code reader, hand held keyboard, or other similar
device. The computer then sets the light levels and colors in accordance with the stored
information for that product by performing a table look up.

While the above describes the preferred embodiment of the invention, various other modifications and additions will be apparent to those of skill in the art. These modifications are intended to fall within the scope of the following claims.

CLAIMS:

1.        Apparatus for controlling multiple light sources to be mixed to form light of a
predetermined color, said apparatus comprising:

        plural color sensors, for detecting an amount of light emitted from each of said
light sources;

        storage means, for storing predetermined values indicative of a desired amount
of light to be emitted from each of said light sources;

        a processor for comparing the amount of light detected from each of said light
sources with the desired amount of light to be emitted from each of said light sources, and for
adjusting a value input to a power source supplying said light sources in response thereto.

2.        The apparatus of claim 1 wherein said value adjusted is a Pulse Width
Modulated (PWM) signal.

3.        The apparatus of claim 2 wherein said PWM value adjusted is at least one of
an amplitude or a duty cycle of said PWM signal.

4.        The apparatus of claim 1 wherein said processor is connected to a separate
computer, said computer including data and software for controlling the amount of light
emitted from said sources based upon measured conditions and predetermined inputs.

5.        The apparatus of claim 4 wherein said measured conditions are obtained by
inputting a product to be displayed with said light of a predetermined color, and said
predetermined inputs are stored values indicating a predetermined color with which to
display said product.

6.        Apparatus of claim 4 wherein said measured conditions are time.

7.        Apparatus of claim 2 wherein said PWM signal is adjusted to control both the
predetermined color and the intensity of light emitted at said color.

8.          Apparatus of claim 1 for adjusting at least one of the color and intensity of light emitted to display products for sale, said apparatus comprising:

a table of stored values indicative of the desired relative values of each of plural light sources for each type of product to be displayed;

an external interface for accepting from an input device information indicative of a product to be displayed, with said light; and

control logic for performing a table lookup and adjusting the relative intensities of the lights sources to cause said light sources to emit said stored desired values.

9.          The apparatus of claim 8 wherein said input device is a bar code scanner.

10.         Apparatus of claim 1 further comprising a DC/AC converter for separately adjustment of the output current of each of plural Light Emitting Diode (LED) drivers.

1/4



FIG. 1

FIG. 2

3/4



FIG. 3

FIG. 4

# INTERNATIONAL SEARCH REPORT

## A. CLASSIFICATION OF SUBJECT MATTER
IPC 7    H05B33/08

According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)
IPC 7    H05B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

| Category ° | Citation of document, with indication, where appropriate, of the relevant passages | Relevant to claim No. |
|---|---|---|
| Y | US 6 127 783 A (MARSHALL THOMAS M ET AL) 3 October 2000 (2000-10-03) figures | 1-4,7,10 |
| Y | US 4 810 937 A (HAVEL KAREL) 7 March 1989 (1989-03-07) figures 1,2 | 1-4,7,10 |
| A | US 5 783 909 A (HOCHSTEIN PETER A) 21 July 1998 (1998-07-21) | |
| A | EP 0 716 485 A (HUGHES AIRCRAFT CO) 12 June 1996 (1996-06-12) | |

☐ Further documents are listed in the continuation of box C.          ☒ Patent family members are listed in annex.

° Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier document but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

"&" document member of the same patent family

| Date of the actual completion of the international search | Date of mailing of the international search report |
|---|---|
| 23 August 2002 | 03/09/2002 |

| Name and mailing address of the ISA | Authorized officer |
|---|---|
| European Patent Office, P.B. 5818 Patentlaan 2 NL – 2280 HV Rijswijk Tel. (+31-70) 340-2040, Tx. 31 651 epo nl, Fax: (+31-70) 340-3016 | Maicas, J. |

Form PCT/ISA/210 (second sheet) (July 1992)

| Patent document cited in search report | | Publication date | Patent family member(s) | | Publication date |
|---|---|---|---|---|---|
| US 6127783 | A | 03-10-2000 | CN | 1291282 T | 11-04-2001 |
| | | | WO | 0037904 A1 | 29-06-2000 |
| | | | EP | 1056993 A1 | 06-12-2000 |
| US 4810937 | A | 07-03-1989 | CA | 1265575 A1 | 06-02-1990 |
| | | | US | 4797651 A | 10-01-1989 |
| | | | US | 4754202 A | 28-06-1988 |
| | | | US | 4686425 A | 11-08-1987 |
| US 5783909 | A | 21-07-1998 | WO | 9956303 A1 | 04-11-1999 |
| | | | CA | 2328439 A1 | 04-11-1999 |
| | | | EP | 1075706 A1 | 14-02-2001 |
| EP 0716485 | A | 12-06-1996 | CA | 2159842 A1 | 06-06-1996 |
| | | | DE | 69515969 D1 | 04-05-2000 |
| | | | DE | 69515969 T2 | 04-01-2001 |
| | | | EP | 0716485 A1 | 12-06-1996 |
| | | | ES | 2144108 T3 | 01-06-2000 |
| | | | IL | 116239 A | 28-10-1999 |
| | | | JP | 8228026 A | 03-09-1996 |
| | | | US | 5736881 A | 07-04-1998 |